# Codehost BrightQ Pro Test Page 1/2

This document was printed using Codehost BrightQ Pro


## Codehost, Inc.

**THE SOFTWARE BEHIND SMART HARDWARE**

**http://www.codehost.com**



Codehost, BrightQ, BrightQ SE, BrightQ Professional and BrightQ Pro are either registered trademarks or filed trademarks of Codehost, Inc. in the United States and other countries.

Copyright 1999–2013 Codehost, Inc.

# Codehost BrightQ Pro Test Page 2/2

### Codehost BrightQ Pro Configuration Tool

```
Usage: codehost-config [ARGS]
ARGS can be :
    --help | -h                   Print this help message
    --version | -v                Print version information and exit
    --fast | -f                   Fast start-up; do not fetch initial status information
                                  Implied for non-interactive commands.
    --add | -c <queue> <ppd>      Configure a new printer
    --add-class | -A <class> <queue1> [queue2] ...
                                  Configure a class from existing queues or classes.
                                  Only available on CUPS and System V systems.
    --remove  | -r <queue>        Remove a queue or class from the system
    --remove-member | -R <class> [queue1] [queue2] ...
                                  Remove one or more queue/class from an existing class.
                                  If none are specified, all members from the class are removed.
    --update  | -u <queue>        Update the parameters for a queue
    --config  | -C <queue>        Show available options for the queue
    --default | -d <queue>        Make the queue the system default
    --system  | -s option=value   Set a printing system option
    --list | -a                   List all available queues

Optional arguments :
    --login | -l <login>          Specify a user for authentication
    --pass  | -p <password>       Specify a password for the user
    --description | -D <desc>     Add/update a description for the printer
    --location | -L <location>    Add/update the location for the printer
    --uri | -U <URI>              Set the connection URI for the printer
    --options | -o <options>      Change the default PPD settings
    --use-pjm y|n                 Whether to use the PJM GUI for the printer
```

### Codehost Print Job Manager

```
Usage: (pjm|lpr) [ options ] [ filename ]
Options common to both LPR and SysV Styles
    --no-gui                    Do not present the normal BrightQ Pro PJM GUI
    -o <option=value[,option=value...]>   Set ppd options
    -n #                        Number of copies
    -d <queue>                  Select print queue
    -c                          Print a copy
    filename                    If  present,  print  this  file.
                                Otherwise,  print information presented on stdin.
```

### Codehost License Manager

```
Usage: codehost-license [ARGS]
ARGS can be :
   --help | -h                    Print this help message
   --import | -i licence.cl[f|p]  Import a license file
   --machineid | -m               Print out the Machine ID for this computer
   --online | -o                  Online product registration
   --activation | -a              Online product activation
   --certificate | -c CERT        Specify the certificate number for activation
   --email | -e your@email.com    Specify the user account for activation
   --password | -p password       Specify the password for the user account
```